

TIME LED[®]

Comma Range: 15W LED Round Bulkhead

Installation and Operating Instructions



Read and follow instructions before operating your light.
Save this manual for future reference.

Package includes:

- 1 x 15W LED Round Bulkhead
- 1 x Manual

Safety:

- This bulkhead must be earthed.
- Before installation or maintenance, ensure that the mains supply to the bulkhead is switched off and the circuit supply fuses are removed or circuit breaker turned off.
- Check that the total load on the circuit, including when this bulkhead is fitted, does not exceed the rating of the circuit cable fuse of the circuit breaker.

Installation of this luminaire should only be carried out by a qualified electrician or competent person to the current Building and IEE Wiring Regulations (BS7671).

INS-780596-V2

TIME LED is part of Pitacs Limited. For customer support contact:

Bradbourne Point, Bradbourne Drive, Tilbrook, Milton Keynes, Buckinghamshire MK7 8AT

T: +44 (0)1908 271155 F: +44 (0)1908 640017 E: info@timeled.co.uk W: www.timeled.co.uk



Product Code	780596
Size (mm)	284x75
Lamp	SMD
Watts	15W
Equivalent Watts	120W
Lumens	1100lm
IP Rating	IP65
Colour Temp	CCT Adjustable: 4000K-5000K

Beam Angle	120°
Material	Mixed PC
Dimmable	No
Voltage/Hertz	220-240V 50/60Hz
Lifespan	25,000 hours
Warranty	3 Years
Energy Rating	A

Instructions for new installations:

- 1) Remove the diffuser and front bezel from the base by turning anti-clockwise.
- 2) Loosen the 3 retaining screws on the gear tray, and rotate anti-clockwise to align the screw heads with the large aperture of the keyhole slots. When aligned, the gear tray can be lifted away from the base.
- 3) Prepare the mains supply cable and the fixings points on the chosen mounting surface, ensuring they are able to support the weight of the bulkhead.
- 4) Pass the mains supply cable through the cable entry hole, attach the base to the mounting surface and secure with the screws provided.

NOTE: To maintain the IP Rating, ensure all fixing points and cable entry points are sealed.

- 5) Route the mains supply cable to the terminal block on the gear tray, ensuring correct polarity is maintained.
- 6) Refit the gear tray to the base (opposite of point 2) and secure by fitting the screws.
- 7) Refit the diffuser and front bezel by rotating clockwise.
- 8) Reconnect the mains and check for accurate function.

Colour Temperature Switch:

When the LED board is exposed, use the switch located on the board to switch between colour temperatures of 4000K and 5000K.

Warning: Only operate CCT switch when power is switched off.

Cleaning:

- Do not use any chemical or abrasive cleaners.
- Clean product with only a soft dry cloth.
- Clean product at regular intervals.

Warning:

- This product is not a toy and contains small parts.
- This product is unsuitable for installation in or near coastal and marine environments.

Warranty:

- This product is warranted to be free of defects in materials, design and workmanship for 3 years from the date of purchase (conditions apply, please see TIME LED website for further details). If a suspected fault should develop in this time, please contact us via the address on the front.

Recycling Advice:

Waste Electrical products should not be disposed of with household waste. Please recycle where facilities exist. Check with your local authority or retailer for recycling advice.

Full Technical specification available upon request. Contact info@timeled.co.uk for PDF.

TIME LED®

Comma Range: 15W LED Round Bulkhead