

Warning:

- Before installation and servicing, disconnect the electricity supply at the mains. Carefully observe all instructions or warnings that are labelled in, or supplied with, your product.
- Keep the device away from fire.
- Do not attempt to disassemble the garden light.

Cleaning:

- Do not use solvents or abrasive cleaners as these could damage the finish.
- In normal circumstances, stainless steel is very resistant to corrosion. It does however require maintenance to preserve the high-quality appearance. Wash the product with warm soapy water, removing all surface deposits. Rinse with clear water and with a soft cloth, wipe dry.
- Do not clean the units with a pressure washer.

If in any doubt, consult a qualified electrician.

Important information:

- Not recommended for use on delicate floors.

Recycling Advice:

Waste electrical products should not be disposed of with household waste. Please recycle where facilities exist. Check with your Local Authority or retailer for recycling advice.

TIME LED®

Landscape LED Garden Bollard Light (80cm)

Installation and Operating Instructions



Read and follow instructions before operating your light.
Save this manual for future reference.

Package includes:

- 1 x Landscape Garden Bollard Light (80cm)
- 1 x Manual

*Lamp not included

INS-778326-V2

TIME LED is part of Pitacs Limited. For customer support contact:

Bradbourne Point, Bradbourne Drive, Tilbrook, Milton Keynes, Buckinghamshire MK7 8AT
T: +44 (0)1908 271155 F: +44 (0)1908 640017 E: info@timeled.co.uk W: www.timeled.co.uk

Full Technical specification available upon request. Contact info@timeled.co.uk for PDF.

TIME LED®

Landscape LED Garden Bollard Light (80cm)



Product Code	778326	Material	Stainless Steel & PC Cover
Size (mm)	125x120x800mm	Voltage	230-240V
Fitting	E27	Hertz	50/60Hz
Max Wattage	15W Max	IP Rating	IP44

Features and Benefits:

- Perfect for outdoor use
- Durable stainless steel & polycarbonate
- LED Compatible
- Recommended Lamp: 8W LED ES/E27

Important information:

- This fitting must be mounted on either a concrete surface or a paving slab that has been concreted in position
- Plan the desired layout of this fitting carefully, ensuring the cables will reach the distance between the junction box and the light fitting.
- Avoid locating any cables in positions that would cause a hazard. Position cables and outdoor rated junction boxes (not supplied) away from areas where they may be at risk from being cut, trapped or damaged.
- Cables must be protected using suitable conduit or plastic trunking.
- When changing a lamp, always switch off at the mains and allow the lamp to cool before handling. Dispose of used lamp carefully. Do not exceed the wattage stated or use a different shape lamp from that indicated on the fitting.

Installation:

Existing fittings must be completely removed before installation of a new product. Before removing the existing fitting, carefully note the position of each set of wires.

- 1) Using the base plate as a template, mark the fixing holes onto the mounting surface.
- 2) Drill holes to the necessary size and depth - taking care not to damage any concealed pipes or wiring below the mounting surface.
- 3) We recommend fitting this product with expanding bolt type fixings which are suitable for use on most surfaces, however alternative fixings may be required.
- 4) Push the fixing bolts into the mounting holes and secure.

