TIME LED®

Ambient 40W LED 12V Driver

Installation and Operating Instructions



Read and follow instructions before operating your driver. Save this manual for future reference.

Package includes: 1 x Ambient 40W LED 12V Driver 1 x Manual

Safety:

• This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS 7671) and current Building Regulations. If in any doubt, consult a qualified electrician.

- Please isolate mains prior to installation or maintenance
- Check the total load on the circuit (including when this product is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker
- Do not overload this product or subject it to conditions outside its rating
- Please note the IP (Ingress Protection) rating of this luminaire when deciding the location for installation
- This product is IP20 rated

INS-781234-V1

TIME LED is part of Pitacs Limited. For customer support contact:

Bradbourne Point, Bradbourne Drive, Tilbrook, Milton Keynes, Buckinghamshire MK7 8AT

T: +44 (0)1908 271155 F: +44 (0)1908 640017 E: info@timeled.co.uk W: www.timeled.co.uk













Product Code	781234
Size (mm)	160x20x58
Watts	40W
Input Frequency	50Hz
Voltage	170-265V
Hertz	50Hz
Current	3.33A

Power	40W
Power Factor (PF)	0.9
Material	PC
IP Rating	IP20
Warranty	1 Year

Installation:

- · Provide power to the required point of installation.
- Connect the LED driver to the mains supply, ensuring the correct polarity is observed: Live = brown, Neutral = blue.

• Connect a suitable LED load to the secondary side of the driver, ensuring the correct polarity is observed: Red to positive (+) and Black to negative (-).

- Ensure cable strain relief is securing the cables effectively.
- Switch on power supply and check for correct operation.

Cleaning:

Clean with a soft dry cloth only, do not use aggressive cleaning products or solvents which may damage the driver.

Warning:

• This product must be disconnected from the circuit if subjected to any high voltage or insulation resistance testing. Irreparable damage will occur if this instruction is not followed.

Warranty:

• This product is warranted to be free of defects in materials, design and workmanship for 1 year from the date of purchase (conditions apply, please see TIME LED website for further details). If a suspected fault should develop in this time, please contact us via the address on the front.

Recycling Advice:

Waste Electrical products should not be disposed of with household waste. Please recycle where facilities exist. Check with your local authority or retailer for recycling advice.

Full Technical specification available upon request. Contact info@timeled.co.uk for PDF.



Ambient 40W LED 12V Driver