

Polar 18W/30W CCT Bulkhead

Installation and Operating Instructions



Read and follow instructions before operating your light.

Save this manual for future reference.

Package includes:

- 1 x Polar 18W/30W CCT Bulkhead
- 1 x Manual

Safety:

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician.
- · Isolate mains prior to installation or maintenance.
- Check the total load on the circuit (including when this luminaire is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker.
- This product is IP64 rated and suitable for interior installations only.
- The LEDs fitted in this product are non-replaceable.
- · This product is non-dimmable.

INS-793473-793480-V2

TIME LED is part of Pitacs Limited. For customer support contact:

Bradbourne Point, Bradbourne Drive, Tilbrook, Milton Keynes, Buckinghamshire MK7 8AT

T: +44 (0)1908 271155 F: +44 (0)1908 640017 E: info@timeled.co.uk W: www.timeled.co.uk


















| Product Code | 793473 793480 |
|--------------------|-----------------------|
| Size (mm) | Ø280 x 60 Ø330 x 60 |
| Watts | 18W 30W |
| Equivalent Wattage | 90W 150W |
| Lumens | 1620lm 2700lm |
| IP Rating | IP64 |
| Dimmable | No |
| Lifespan | 20,000 hours |
| Material | PC |

| Net Weight | 0.76kg 0.92kg |
|-----------------|--------------------------------------|
| Voltage | 220V |
| Input Frequency | 50Hz |
| Current (A) | 135mA |
| Colour Temp | CCT Adjustable: 3000K/4000K/6000K |
| Beam Angle | 120° |
| Energy Rating | A+ |
| Warranty | 2 Years |

Instructions for new installations:

- Isolate mains power near location so as not to cause an electrical hazard before installation.
- 2) Remove all packaging material.
- **3)** Attach mounting plate in desired location with cable through centre.
- Select desired colour temperature with CCT switch and terminate cable to terminal block in Polar Bulkhead
- 5) Twist Polar Bulkhead to mounting plate completely to ensure seal.
- **6)** Reconnect mains power and check for correct operation.

Typical Mounting:



Cleaning:

- · Do not use any chemical or abrasive cleaners.
- · Clean product with only a soft dry cloth.

Warning:

- This product shall be installed by a licenced electrician in compliance with the requirements set out in AS/NZS 3000 (current edition) and other relevant Standards and Regulations pertaining to the installation.
- This product must only be used for the purpose outlined in this instruction manual.
- Prior to installing this product, check the product has not been damaged during transport. Do not operate/install
 the product if any damage is visible in any way. Return complete product to place of purchase for inspection, repair
 or replacement.

Warranty:

This product is guaranteed against faulty workmanship and material for a period of 2 years from date of installation. TIME LED at its discretion will repair, replace or offer a refund for any defective product. Any alterations or modifications to this product without permission will void warranty. TIME LED will not be responsible for cost of removing, retrieving, reinstalling and installation of any replacements.

Recycling Advice:

Waste Electrical products should not be disposed of with household waste. Please recycle where facilities exist. Check with your local authority or retailer for recycling advice.

Full Technical specification available upon request. Contact info@timeled.co.uk for PDF.

